

## DESCRIPTION

## RECORDING MEDIUM, REPRODUCTION DEVICE, PROGRAM

Technical Field

5 [0001]

The present invention relates to a technical field of jump playback.

Background Art

10 [0002]

A jump playback function is to start playback of a digital stream encoded by variable-length coding, from a randomly chosen point in the digital stream. In the case of a video stream encoded using the MPEG2-Video or MPEG4-AVC standard, execution of jump playback requires that all the pictures referenced by a picture located at a jump playback point be supplied to the decoder. How much of the video stream needs to be read in order to supply all the necessary reference pictures to the decoder varies depending on the structure of the GOPs contained in the video stream. An MPEG2-Video stream contains different types of GOPs, such as closed-GOPs and open-GOPs. A closed-GOP uses no reference pictures from any other GOP. Thus, by reading the video stream from a closed-GOP containing a jump playback point, all the necessary reference pictures will be supplied to the decoder.

25 [0003]

Taking an MPEG2-Video stream as an example, an open-GOP

has references not only within the GOP itself but also from an immediately previous GOP. Consequently, in order to execute jump playback from an open-GOP, the playback apparatus needs to start reading the recording medium from the GOP that immediately previous to the target open-GOP and supply the read GOP to the decoder. That is, in order to start playback from an open-GOP, the playback apparatus is required to read the GOP immediately previous to the target open-GOP.

10 [0004]

For executing jump playback, it is necessary to detect an I (Intra) picture located at the start of a GOP. The following patent literature discloses the data structure facilitating I picture detection.

15 Patent Literature 1: JP Patent Application Publication No. 2001-169247 (Application No. 2000-228656)

#### Disclosure of the Invention

Problems the Invention is attempting to Solve

20 [0005]

In the case of an MPEG2-Video stream, an open-GOP uses reference pictures as far as from the immediately previous GOP. In the case of an MPEG4-AVC stream, however, an open-GOP may have a reference to a picture contained in as many as tens of frames before the current frame. It is because the MPEG4-AVC decoder model uses two types of reference pictures, namely short-term reference pictures and long-term reference pictures. A long-term reference

picture may be used by a picture that is located tens of pictures after the long-term reference picture. Thus, reading of the immediately previous GOP is not sufficient to provide the decoder with all the reference pictures  
5 necessary for decoding.

[0006]

In view of the above, the playback apparatus needs to read a large number of pictures in preparation for the worst case. In the worst case, a picture to be decoded  
10 may have a reference to a picture located at the beginning of the video stream. If so, the playback apparatus needs to read all the pictures from the beginning of video stream. Suppose, for example, that the video stream is worth two hours of playback and that a request is made to start playback  
15 from a point corresponds to one hour from the beginning of the video stream. In this case, the playback apparatus is required to read and decode picture data worth one hour of playback time. Thus, it takes a long time before all the necessary reference pictures are ready in the decoder.

20 [0007]

As described above, an MPEG4-AVC video stream requires a long time to execute a jump playback operation. With this drawback, the MPEG4-AVC standard is said not suitable for movie distribution via a recording medium. MPEG4-AVC  
25 streams are said to be most advantageous in the form of stream distribution where the stream is always played back from the beginning. Yet, in view of the advantage of high image quality and high compression rate, it is said to be

a waste to abandon the application of MPEG4-AVC standard to recording media even for the slow response to a jump playback request.

[0008]

5           In view of the above, the present invention aims to provide a recording medium for enabling efficient execution of jump playback starting from an open-GOP using a reference from a previous picture located at quite a number of pictures away.

10

Means for Solving the Problems

[0009]

15           In an attempt to achieve the above aim, the present invention provides a recording medium having a video stream and an entry map recorded thereon. The entry map indicates a plurality of entry points in the video stream, in one-to-one correspondence with a plurality of entry times and flags. Each flag indicates whether a picture located at a corresponding entry point is for causing decoder refresh.

20

Effects of the Invention

[0010]

25           According to the present invention, each flag recorded on the recording medium is associated with a picture located at an entry point and indicates whether the associated picture is an intra picture that causes decoder refresh in the decoding process. With reference to the flags associated with the respective entry points, the playback

apparatus is enabled to distinguish which of the pictures are intra pictures that would cause decoder refresh. Even in the case where an open-GOP has a reference to a number of pictures away, the long-term reference does not go beyond any picture at which the decoder is to be refreshed. Thus, when executing jump playback, the playback apparatus reads up to the first previous picture causing decode refresh. Consequently, it is ensured that all the reference pictures necessary for decoding is supplied to the decoder.

10 [0011]

Suppose, for example, that a video stream is worth two hours of playback and jump playback is to be executed from a playback point corresponding to one hour of playback time from the stream start point. In order to execute such jump playback, reading from the first previous picture that would cause decoder refresh is sufficient to supply all the necessary reference pictures to the decoder. If such a picture is present at a point corresponding to fifteen minutes before the requested playback point, data that needs to be read is reduced from data worth one hour to data worth fifteen minutes. As a result, reference pictures necessary for decoding the picture at the requested jump playback point will be ready in the decoder sooner than in a conventional technique. With this improvement, the MPEG4-AVC format is applicable to a wider variety of uses, including movie distribution via recording media.

25 [0012]

The present invention achieves to efficiently execute

trick play of a video stream that is compressed to contain IDR pictures at relatively long intervals, such as 15 or 30 minutes of playback time, for the sake of high compression rate. That is to say, trick play is efficiently executed without seriously compromising the advantage achieved by high compression rate.

#### Best Mode for Carrying Out the Invention

[0013]

#### 10 (FIRST EMBODIMENT)

The following describes an embodiment of a recording medium according to the present invention. First of all, among various acts of practicing a recording medium of the present invention, an act of using is described. Fig. 1 illustrates a form of using the recording medium according to the present invention. In Fig. 1, a BD-ROM 100 is a recording medium according to the present invention. The BD-ROM 100 is used to supply a movie to a home theater system composed of a playback apparatus 200, a remote controller 300, and a television set 400.

[0014]

This concludes the description of the act of using the recording medium of the present invention. Now, the following describes the act of manufacturing, as one example of acts of practicing the recording medium of the present invention. Fig. 2 illustrates the internal structure of the BD-ROM.

In the figure, the BD-ROM is illustrated on the fourth

level, and the track of the BD-ROM is illustrated on the third level. The track is laterally stretched out, although the track in practice spirals outwards from the center of the BD-ROM. The track is composed of a lead-in area, a volume area, and a lead-out area. The volume area has a layer model of a physical layer, a file system layer, and an application layer. The first level illustrates, in a directory structure, a format of the application layer (application format) of the BD-ROM. As illustrated on the first level, the BD-ROM has a ROOT directory, and the ROOT directory has a BDMV directory.

[0015]

The BDMV directory has three subdirectories called a PLAYLIST directory, a CLIPINF directory, and a STREAM directory.

The STREAM directory stores files with the extension ".m2ts" (e.g. files called "00001.m2ts", "00002.m2ts", and "00003.m2ts") containing data constituting the main body of an individual digital stream.

[0016]

The PLAYLIST subdirectory stores files with the extension ".mpls" (e.g. files called "00001.mpls", "00002.mpls", and "00003mpls").

The CLIPINF directory stores files with the extension ".clpi" (e.g. files called "00001.clpi", "00002.clpi", and "00003.clpi").

<AV Clip Structure>

Next, a description is given of files with the extension ".m2ts". Fig. 3 schematically illustrates the structure of a file with the extension ".m2ts". Each file with the extension ".m2ts" (namely, 00001.m2ts, 00002.m2ts, 00003.m2ts, ...) contains an AV clip. The AV clip (illustrated on the middle level) is created as follows. A video stream (illustrated on the upper first level) containing a plurality of video frames (pictures pj1, pj2, pj3, ...) is converted into PES packets (illustrated on the upper second level). Similarly, an audio stream (illustrated on the upper first level) containing a plurality of audio frames is converted into PES packets (illustrated on the upper second level). The resulting PES packets are further converted into TS packets (illustrated on the upper third level). In addition, the presentation graphics stream carrying text subtitle data (the PG stream illustrated on the lower first level) and the interactive graphics stream carrying interactive composition data (the IG stream illustrated on the lower second level) are converted into TS packets. These TS packets of the video, audio, IG, and PG streams are multiplexed to form the AV clip.

[0017]

Next, a description is given of how an AV clip, which is an MPEG2-TS digital stream, is recorded onto the BD-ROM. Fig. 4 illustrates the process through which TS packets carrying the AV clip are recorded onto the BD-ROM. In Fig. 4, the TS packets of the AV clip are illustrated on the



first level.

As illustrated on the second level, each TS packet of the AV clip is attached with "TS\_extra\_header" (denoted as "EX" in the figure).

5 [0018]

The third and fourth levels illustrate the physical units of the BD-ROM in relation to the TS packets. As illustrated on the fourth level, the track on the BD-ROM is divided into a plurality of sectors. The TS packets each attached with the TS\_extra\_header (hereinafter, simply "EX-TS packets") are divided into groups of 32 EX-TS packets, and each group is written into three sectors of the BD-ROM. Each group composed of 32 EX-TS packets amounts to 6,144 (=  $32 \times 192$ ) bytes, which is equal to the total size of three sectors (=  $2048 \times 3$ ). Each group of 32 EX-TS packets stored in three sectors of the BD-ROM is referred to as an "Aligned Unit". When data is recorded onto the BD-ROM, encryption is carried out in Aligned Units.

[0019]

20 As illustrated on the fifth level, an error correction code is attached to every 32 sectors to constitute an ECC block. As long as accessing the BD-ROM in Aligned Units, the playback apparatus is ensured to obtain a complete set of 32 EX-TS packets. This concludes the description of the process of recording the AV clip onto the BD-ROM.

25

<Video Stream>

The following describes the internal structure of an

MPEG4-AVC video stream. An MPEG4-AVC video stream is composed of a plurality of pictures. Fig. 5A illustrates the plurality of pictures arranged in the coding order.  
[0020]

5        In the figure, the reference numerals "I", "P", and "B" denote an I picture, a P picture, and a B picture, respectively. There are two types of I pictures: one is an IDR picture and the other is a Non-IDR I picture. Non-IDR I pictures, P pictures, and B pictures are encoded using  
10   correlation with other pictures. More specifically, a B picture is composed of Bidirectionally Predictive (B) slices, and a P picture is composed of Predictive (P) slices. There are two types of B pictures: one is a reference B picture, and the other is a non-reference B picture.

15   [0021]

      In Fig. 5A, a Non-IDR I picture is denoted as "I", and an IDR picture is denoted as "IDR". The same denotations are used throughout the following descriptions and figures.

20   <GOP Structure>

      Fig. 5B illustrates the GOP structure of the video stream illustrated in Fig. 5A. As illustrated in the figure, an IDR picture, together with the following B and P pictures, forms a closed-GOP. On the other hand, a Non-IDR I picture,  
25   together with the following B and P pictures, forms an open-GOP.

[0022]

      Fig. 6A illustrates the internal structure of a

closed-GOP. The upper level illustrates the pictures of the closed-GOP in the presentation order, and the lower level illustrates the pictures of the closed-GOP in the coding order. In the coding order, the closed-GOP starts with an IDR picture. In the presentation order, however, the IDR picture is not the first picture in the closed-GOP. Yet, even the pictures other than the IDR picture (B and P pictures) do not rely on any pictures from the previous GOPs. In the figure, an arrow attached with the mark "x" represents that the closed-GOP does not use any reference pictures from the previous GOPs. As described above, a closed-GOP is independent without any reference to the previous GOPs.

[0023]

Fig. 6B illustrates the internal structure of an open-GOP. The upper level of Fig. 6B illustrates the pictures of the open-GOP in the presentation order, and the lower level illustrates the pictures of the open-GOP in the coding order. In the coding order, the open-GOP starts with a Non-IDR I picture. In the presentation order, however, the IDR, Non-IDR I, and P pictures are arranged in a different sequence. More specifically, in the presentation order, B pictures precede the Non-IDR I picture. The B pictures preceding the Non-IDR I picture rely on the previous GOPs. Yet, pictures subsequent to the Non-IDR I picture do not rely on any pictures from the previous GOPs. As described above, an open-GOP may have references to the previous GOPs. This concludes the description of the GOP

structure of an MPEG4-AVC stream.

[0024]

Next, the following describes the internal structures of an IDR picture and a Non-IDR I picture. Fig. 7A illustrates the internal structure of an IDR picture. As illustrated in the figure, the IDR picture is composed of a plurality of Intra slices. Fig. 7B illustrates the internal structure of a Non-IDR I picture. Different from the IDR picture composed solely of Intra slices, the Non-IDR I picture is composed of Intra-, P-, and B-slices. Fig. 7C illustrates the dependencies between the Non-IDR I picture and other pictures. A Non-IDR I picture may be composed of B and P slices and thus may have references to other pictures.

[0025]

Fig. 8 illustrates the dependencies that a Non-IDR I picture may have. The first level illustrates a sequence of pictures in the presentation order. The second level illustrates a sequence of pictures in the coding order. Arrows in the figure schematically represent references that the Non-IDR I picture may have. Although some pictures are referenced over a relatively long period, no picture is referenced beyond an IDR picture. It is because an IDR picture requires decoder refresh, so that all the reference pictures stored on the decoder are erased. Thus, no Non-IDR I picture has references beyond an IDR picture.

<IDR picture>

The following describes the technical significance of inserting IDR pictures in a video stream. An IDR picture forms a closed-GOP and is not located at fixed unit intervals, such as every GOP. The number and locations of IDR pictures contained in a single video stream vary depending on the encoding condition. Depending on the encoding condition, a video stream may contain relatively few IDR pictures or relatively many IDR pictures. Since an IDR picture is encoded without using any short-term and long-term reference pictures, the video stream containing a larger number of IDR pictures achieves lower compression rate. Thus, the compression rate decreases with the increase in the number of IDR pictures. Yet, the presence of at least one IDR picture in the video stream significantly helps to efficiently execute trick play starting from a randomly chosen point in the video stream.

[0026]

Suppose, for example, a P picture needs to be decoded to execute trick play. In this case, it cannot be determined up to how many previous pictures in the video stream need to be decoded in order to decode the P picture. It is because the target P picture may have references to a previous B picture, and the B picture may in turn have references to another previous B or P picture in the coding order. Thus, there is no fixed rule as to how many previous pictures need to be decoded for correctly decoding the target P picture. Yet, if the video stream contains IDR pictures at appropriate points, it is known that inter-picture dependencies do not

exist across any IDR picture. Thus, decoding of up to the nearest preceding IDR picture ensures that all the pictures necessary for playback of the target P picture is supplied to the decoder. In this way, decoding of a P picture in  
5 trick play execution is facilitated. As a consequence, fast-speed playback of the video stream, which involves sequential decoding of I and P pictures, is readily executed.  
[0027]

As described above, the number and locations of IDR  
10 pictures in a single video stream are determined in accordance with the encoding condition. In the determination, it is important to consider both the efficiency of trick play and compression rate. The description of the present embodiment is given on  
15 precondition that IDR pictures are located at relatively long time intervals, such as fifteen-minute or thirty-minute intervals.

#### <Recording to BD-ROM>

20 Next, the following describes how IDR pictures and Non-IDR I pictures are converted into TS packets and recorded onto the BD-ROM. Fig. 9 illustrates the process through which an IDR or Non-IDR I picture is converted into TS packets. In the figure, the first level illustrates an IDR or Non-IDR  
25 I picture. The second level illustrates an Access Unit stipulated according to MPEG4-AVC. A plurality of slices constituting the IDR or Non-IDR I picture is arranged in a sequence. Then, AUD (Access Unit Delimiter), SPS

(Sequence Parameter Set), PPS (Picture Parameter Set), and SEI (Supplemental Enhanced Information) are attached to the slice sequence. In this way, the picture slices are converted into an Access Unit.

5 [0028]

AUD, SPS, PPS, SEI, and Access Unit mentioned above are information all stipulated according to MPEG4-AVC and described in various documents, such as "ITU-T Recommendation H.264". For the details, such documents  
10 should be referenced. The point in this description is that AUD, SPS, PPS, and SEI need to be supplied to the playback apparatus for executing random access to the video stream.

The third level illustrates NAL units. AUD, SPS, PPS, SEI, and slices illustrated on the second level are  
15 separately attached with a header to be converted into separate NAL units. NAL units are supported by the Network Abstraction Layer (NAL) stipulated according to MPEG-4 AVC and described in various documents, such as "ITU-T Recommendation H.264". For the details, such documents  
20 should be referenced. The point in this description is that AUD, SPS, PPS, SEI, and each slice are converted into separate NAL units and manipulated independently in the Network Abstraction Layer.

[0029]

25 As described above, the single picture is converted into a plurality of NAL units. Then, the NAL units are converted into PES packets illustrated on the fourth level, and the PES packets are converted into TS packets. Finally,

the resulting TS packets are recorded onto the BD-ROM.

In order to play back one GOP, the playback apparatus needs to supply the decoder with a NAL unit containing AUD of the first IDR or Non-IDR I picture in the GOP. That is, the NAL unit containing AUD is used as an index for decoding the IDR or Non-IDR I picture. In this embodiment, each NAL unit containing AUD is regarded as a point. For playback of the video stream, the playback apparatus recognizes each of such a point as an entry point for executing playback of an I picture. Consequently, for execution of jump playback to a randomly access point in the AV clip, it is extremely important for the playback apparatus to recognize the locations of AUDs of IDR and Non-IDR I pictures. This concludes the description of the structure of the MPEG-4AVC video stream.

#### <Clip information>

Next, the following describes files with the extension ".clpi". Each file with the extension ".clpi" (e.g. 00001.clpi, 00002.clpi, 00003.clpi,...) contains Clip information. Each piece of Clip information is management information of an individual AV clip. Fig. 10 illustrates the internal structure of a piece of Clip information. As illustrated in the left block of the figure, the Clip information is composed of the following fields:

(i) "ClipInfo()" storing the attributes of the AV clip file;

(ii) "Sequence Info()" storing information related



to the ATC sequence and STC sequence;

(iii) "Program Info()" storing information related to the program sequence; and

(iv) "Characteristics Point Info (CPI ())".

5        Leader lines *cul* in the figure indicates that the structure of the *i*-th program sequence (Program Sequence(*i*)) is illustrated in greater detail. As indicated by the leader lines *cul*, the Program Info associated with the Program Sequence(*i*) is composed of the  
10    total number of *Ns*(*i*) pairs of Stream\_PID and Stream\_Coding\_Info (in the figure, Stream\_PID[*i*](0) and Stream\_Coding\_Info(*i*, 0)-Stream\_PID[*i*](*Ns*(*i*) - 1) and Stream\_Coding\_Info(*i*, *Ns*(*i*)-1)).

[0030]

15        The Stream\_PID is a packet identifier of an individual packet carrying an elementary stream constituting the AV clip. The Stream\_Coding\_Info indicates the coding standard used to encode the elementary stream.

Fig. 11A illustrates the Stream\_Coding\_Info  
20    associated with the video stream, whereas Fig. 11B illustrates Stream\_Coding\_Info associated with the audio stream. The Stream\_Coding\_Info is composed of the following fields: "stream\_coding\_type" indicating the coding method of the video stream is either MPEG4-AVC or  
25    MPEG2-Video; "video\_format" indicating the video format is 480i, 576i, 480p, 1080i, 720p, or 1080p; "frame\_rate" indicating the frame rate of the video stream is 23.976Hz, 29.97Hz, or 59.94Hz; and "aspect\_ratio" indicating the

aspect ratio of the pictures is 4:3 or 16:9.

[0031]

Fig. 11B illustrates the Stream\_Coding\_Info associated with the audio stream. As illustrated in the figure, the Stream\_Coding\_Info associated with the audio stream is composed of the following fields: "stream\_coding\_type" indicating the coding type of the audio stream is LPCM, Dolby-AC3, or Dts; "audio\_presentation\_type" indicating the presentation type of the audio stream is stereo channel, mono channel, or multi-channel; "sampling\_frequency" indicating the sampling frequency of the audio stream; and "audio\_language" indicating a language code of the audio stream.

15 [0032]

With reference to the Stream\_Coding\_Info, the playback apparatus is enabled to identify which of the elementary streams contained in an AV clip are MPEG4-AVC streams.

20 <CPI(EP\_map)>

Next, a description of CPI is given with reference to Fig. 10 again. Leader lines cu2 in the figure indicates that the structure of CPI is illustrated in greater detail. As illustrated in the leader lines cu2, the CPI is composed of a plurality of EP\_map fields. Each EP\_map is composed of Ne pieces of EP\_map\_for\_one\_stream\_PID (namely, EP\_map\_for\_one\_stream\_PID(0)-(Ne-1)). Each piece of EP\_map\_for\_one\_stream\_PID is an EP\_map associated with one

of elementary streams contained in the AV clip. An EP\_map is information indicating entry points set on the associated elementary stream. An entry point is where the Access Unit Delimiter of an I picture is present. The EP\_map indicates the packet number of each entry point (SPN\_EP\_start) and the corresponding entry time (PTS\_EP\_start). Leader lines cu3 in the figure indicates that the internal structure of EP\_map\_for\_one\_stream\_PID is illustrated in greater detail.

10 [0033]

As illustrated in the figure, the EP\_map\_for\_one\_stream\_PID is composed of  $N_c$  pieces of EP\_High (EP\_High(0)-(Nc-1)) and  $N_f$  pieces of EP\_Low (EP\_Low(0)-(Nf-1)). Here, the EP\_High holds the most significant bits of the SPN\_EP\_start and PTS\_EP\_start of an I picture. The EP\_Low holds the least significant bits of the SPN\_EP\_start and PTS\_EP\_start of the I picture.

Leader lines cu4 in the figure indicate that the internal structure of the EP\_High is illustrated in greater detail. As illustrated in the leader lines cu4, EP\_High(i) is composed of the following fields: "ref\_to\_EP\_Low\_id[i]" which is a reference value to the EP\_Low; "PTS\_EP\_High[i]" indicating the most significant bits of the PTS for the I picture; and "SPN\_EP\_High[i]" indicating the most significant bits of the SPN for the I picture. Here, the reference numeral "i" denotes an identifier uniquely identifying an arbitrary EP\_High field.

[0034]

Leader lines *cu5* in the figure indicate that the EP\_Low structure is illustrated in greater detail. As indicated by the leader lines *cu5*, the EP\_Low is composed of the following fields: "*is\_angle\_change\_point* (EP\_Low\_id)";  
5 "*I\_end\_position\_offset* (EP\_Low\_id)" indicating the size of the associated I picture; "*PTS\_EP\_Low*(EP\_Low\_id)" indicating the least significant bits of the PTS of the associated I picture; and "*SPN\_EP\_Low*(EP\_Low\_id)" indicating the least significant bits of the SPN of the  
10 associated I picture. Here, the "EP\_Low\_id" denotes an identifier uniquely identifying an arbitrary EP\_Low field.  
[0035]

The data structure of the EP\_map as described above is basically disclosed, for example, in the above patent  
15 literature. Thus, no further description is given in this specification. Yet, the flag called "*is\_angle\_change\_point*" is one feature of the present invention and thus will be described in detail.

The "*is\_angle\_change\_point*" is a flag indicating  
20 whether the I picture specified as an entry point serves as a point where the playback apparatus can enter to the AV clip from other AV clips. Fig. 12 illustrates the concept of entering to an AV clip and exiting from the AV. Here, the process of entering to an AV clip refers to the seek  
25 process of causing the optical pickup to move from the current TS packet contained in the current AV clip to a TS packet contained in another AV clip. An arrow *er1* illustrated in Fig. 12 schematically represents the movement of the

optical pickup at the time of entering to the AV clip. Each TS packet specified by the *is\_angle\_change\_point* field set to the value "1" is judged as a permissible entering point. [0036]

5       The TS packet immediately preceding a TS packet specified by the *is\_angle\_change\_point* field set to the value "1" is judged as an exit point to the AV clip. Here, the process of exiting from an AV clip refers to a seek process of causing the optical pickup to move from the  
10       currently reading TS packets contained in the current AV clip to a TS packet contained in another AV clip. An arrow ex1 illustrated in Fig. 12 schematically represents the movement of the optical pickup exiting from the AV clip. [0037]

15       At the time of entering to an AV clip from another AV clip, the decoder cannot use any pictures obtained through the decoding process having been conducted by that time. Thus, the I picture specified as an entry point by the *is\_angle\_change\_point* field set to the value "1" must be  
20       an IDR picture. That is, the "*is\_angle\_change\_point*" set to the value "1" indicates that the specified I picture is an IDR picture. The "*is\_angle\_change\_point*" set to the value "0" indicates that the specified I picture is a Non-IDR I picture. The process illustrated in the figure, i.e.  
25       the process of "exiting" from the currently played AV clip and "entry" to another AV clip is referred to as "angle\_change".       The field is named "*is\_angle\_change\_point*" in view of that the field specifies

a point where "angle\_change" is possible. It should be noted, however, that provision of the EP\_map having the *is\_angle\_change\_point* field set to "1" is not sufficient to implement the angle change process. The implementation

5 of the angle change process additionally requires improvements on AV clips and PlayList information. The improvements of AV clips and PlayList information necessary for implementing the angle change will be described later in detail in a second embodiment of the present invention.

10 Thus, such description is omitted in this embodiment.

[0038]

It should be noted, in addition, that the EP\_map is expressed as a pair of EP\_High and EP\_Low values in terms of the data structure. Yet, for the sake of simplicity

15 of the description, unless specifically noted, the most significant bits and least significant bits of the PTS indicated by EP\_High and EP\_Low are collectively denoted as PTS\_EP\_start. Similarly, the most significant bits and least significant bits of the SPN indicated by EP\_High and

20 EP\_Low are collectively denuded as SPN\_EP\_start.

The following describes how the EP\_map associated with the video stream illustrated in Figs. 5 and 8 is set. Fig. 13 illustrates the setting of the EP\_map associated with the video stream illustrated in Fig. 5. The first level

25 illustrates a sequence of a plurality of pictures arranged in the presentation order. The second level illustrates the timeline for the picture sequence. The fourth level illustrates a plurality of TS packets stored on the BD-ROM.

The third level illustrates the EP\_map setting. Suppose that I pictures are located at points  $t_1$ ,  $t_2$ ,  $t_3$ ,  $t_4$ , and  $t_5$  on the timeline illustrated on the second level. The PTS\_EP\_start fields of the EP\_map are set to the value specifying the points  $t_1$ - $t_5$ . The Access Unit Delimiters of the video stream stored on the BD-ROM are located at points  $n_1$ ,  $n_2$ ,  $n_3$ ,  $n_4$ , and  $n_5$  in the TS packet sequence. The SPN\_EP\_start fields of the EP\_map are set to the value specifying points  $n_1$ - $n_5$ . Among entry points #1-#5 corresponding to the points  $t_1$ - $t_5$  and thus to the points  $n_1$ - $n_5$ , pictures located at entry points #1 and #3 are IDR pictures. Thus, for entry points #1 and #3, the *is\_angle\_change\_point* is set to the value "1". Regarding the other entry points, namely entry points #2, #4, and #5, the *is\_angle\_change\_point* is set to the value "0".

[0039]

Fig. 14 shows, in tabular form, pairs of EP\_Low and EP\_High values indicating the PTS\_EP\_start and the SPN\_EP\_start of entry points #1-#5 illustrated in Fig. 13. In Fig. 14, the left table shows the values of EP\_Low and the right table shows the values of EP\_High.

In Fig. 14, the left table shows  $EP\_Low(0)-(Nf - 1)$ . The  $EP\_Low(i)-(i + 1)$  values of the PTS\_EP\_Low indicate the least significant bits of the points  $t_1$ - $t_5$ , respectively. The  $EP\_Low(i)-(i + 1)$  values of the SPN\_EP\_Low indicate the least significant bits of the points  $n_1$ - $n_5$ , respectively. Among the *is\_angle\_change\_point(i)-(i + 1)*, each of the *is\_angle\_change\_point(i)* and the *is\_angle\_change\_point(i*

+ 2) is set to the value "1" because the corresponding I picture is an IDR picture. On the other hand, each of the *is\_angle\_change\_point(i + 1)*, *(i + 3)*, and *(i + 4)* is set to the value "0" because their corresponding pictures are

5 Non-IDR I pictures.

[0040]

The right table in Fig. 14 shows the values of *EP\_High(0)-(Nc - 1)* set in the *EP\_map*. Provided that the points *t1-t5* commonly have the same set of most significant bits and the points *n1-n5* commonly have the same set of most significant bits, the values of *PTS\_EP\_High* and *SPN\_EP\_High* are set to the respective sets of most significant bits. In addition, the *ref\_to\_EP\_Low\_id* is set to specify the first *EP\_Low* field (*EP\_Low(i)*) out of the *EP\_Low* fields indicating the points *t1-t5* and *n1-n5*. With this setting, the *EP\_High* indicates the common most significant bits of the *PTS\_EP\_start* and the common most significant bits of the *SPN\_EP\_start*.

15 [0041]

20 The most significant feature of such *EP\_map* lies in that the data required to be read to execute jump playback is kept to a minimum. Fig. 15 illustrates the range of data required to be read to execute jump playback.

Suppose, for example, jump playback is to be executed so as to start playback from the point corresponding to *In\_time* illustrated in the figure. When the point corresponding to the *In\_time* is a jump playback point, the playback apparatus locates the nearest one of the entry



point preceding the jump playback point and with the *is\_angle\_change\_point* set to the value "1". In the figure, the entry point corresponding to the temporal point *t3* has the *is\_angle\_change\_point* set to the value "1". Thus, the playback apparatus retrieves the value of the *SPN\_EP\_start* = *n3* of entry point #3 that corresponds to the *PTS\_EP\_start* = *t3*. The playback apparatus then reads the TS packets carrying the AV clip, starting from the point *n3* and supplies the read TS packets to the decoder. With this arrangement, the playback apparatus is enabled to supply to the decoder all the reference pictures necessary for decoding the I picture. That is, the need is eliminated to read the TS packets all the way from the beginning of the video stream.

[0042]

Suppose, for example, that the video stream is worth two hours of playback time and that playback is to be started from a playback point whose *In\_time* corresponds to one hour from the start of the video stream. In this example, the temporal point *t3* corresponds to fifteen minutes before the *In\_time*. Thus, by reading the preceding pictures up to the temporal point *t3*, the playback apparatus is enabled to supply all the reference pictures necessary for executing the jump playback to the decoder.

That is, when executing jump playback to start playback from the point corresponding to the *In\_time* which is "one hour after" the start of the video stream, the playback apparatus starts reading the pictures at most from the point corresponding to fifteen minutes before the temporal point

t3. As a result, all the reference pictures necessary for the decoding process are duly supplied to the decoder. In this manner, playback of an MPEG4-AVC video stream stored on a BD-ROM can be started from any given point on the video stream by reading a minimum range of the stream data. This advantageous feature helps to use the MPEG4-AVC format for movie distribution via BD-ROM and thus significantly increases the usage of the MPEG4-AVC format.

[0043]

In the following description, a comparison is made in data structure between the EP\_map for an MPEG4-AVC stream and the EP\_map for an MPEG2-Video stream. Both the EP\_map for an MPEG4-AVC stream and the EP\_map for an MPEG2-Video stream commonly show the relationships between the SPN and PTS values of I pictures. The difference lies in that the EP\_map for an MPEG4-AVC stream includes the *is\_angle\_change\_point* field indicating whether the associated I picture is an IDR picture or a Non-IDR I picture. The EP\_map of an MPEG4-AVC stream indicates, for each of IDR and Non-IDR I pictures, the *is\_angle\_change\_point* field in addition to a pair of SPN and PTS. Furthermore, the EP\_map for an MPEG4-AVC stream is compatible with the EP\_map for an MPEG2-Video stream. Owing to the compatibility between the EP\_map for an MPEG4-AVC stream and the EP\_map for an MPEG2-Video stream, BD-ROM creators are allowed to choose either of the MPEG2-Video and PEG4-AVC standards without giving any consideration to the EP\_map structure. Consequently, a choice between the MPEG2-Video and

MPEG4-AVC standards can be made relatively freely without being bound to EP\_map structure. That is to say, the BD-ROM creators are offered wider variety of options in the selection of codec standard.

5 [0044]

This concludes the description of the Clip information according to the present embodiment. Next, a description is given of files with the extension "mpls".

#### 10 <PlayList Information>

Each file with the extension "mpls" (00001.mpls, 00002.mpls, 00003.mpls ...) stores PlayList information. PlayList information defines a playback path called a PlayList that uses elementary streams. Fig. 16 illustrates the data structure of PlayList information. As illustrated in the middle block of the figure, the PlayList information is composed of a plurality of pieces of PlayItem information. A PlayItem defines a playback section by specifying a pair of In\_time and Out\_time on at least one AV clip timeline. With a plurality of pieces of PlayItem information, the PlayList information defines a PlayList (PL) composed of multiple playback paths. The dashed lines *hs1* in the figure indicates that the internal structure of the PlayItem information is illustrated in greater detail. As illustrated in the figure, the PlayItem information is composed of the following fields: "Clip\_information\_file\_name" indicating the name of a file containing the associated Clip information;

"Clip\_codec\_identifier" indicating the coding type of the associated AV clip; and "In\_time"; and "Out\_time. Fig. 17 illustrates the relationship between the AV clip and the PlayList information. The first level illustrates the timeline of the AV clip. The second level illustrates the timeline of the PlayList information (hereinafter, PL timeline). The PlayList information contains three pieces of PlayItem information called PlayItem #1, #2, and #3. The In\_time and Out\_time of the respective pieces of PlayItem information define three playback sections. By linearly aligning the three playback sections, a timeline that is different from the AV clip timeline is defined. This timeline is the PL timeline illustrated on the second level. As described herein, with the use of PlayItem information, a different timeline from the AV clip timeline is defined.

[0045]

As described above, the EP\_map contained in the Clip information indicates, for each I picture contained in the video stream, a pair of SPN and PTS values of the I picture along with whether the I picture is an IDR picture. Since the EP\_map enables the playback apparatus to efficiently execute trick play starting from a given temporal point, the PlayList information is expressed using time information on precondition that trick play can be efficiently executed. This expression ensures the compatibility in data structure between the PlayList information on the BD-ROM and the PlayList information on

a rewritable recording medium (BD-RE).

[0046]

This concludes the description of the internal structure of the PlayList information according to the present embodiment and thus concludes the description of the recording medium according to the present invention. Next, a description is given of the playback apparatus according to the present invention.

#### 10 <Internal Structure of Playback Apparatus>

Fig. 18 illustrates the internal structure of the playback apparatus. Based on the internal structure illustrated in the figure, playback apparatuses consistent with the present invention are industrially manufactured.

15 The playback apparatus of the present invention is roughly composed of two parts, one of which is a system LSI and the other is a drive device. By mounting those parts into a device cabinet and onto a substrate, the playback apparatus can be manufactured industrially. The system LSI is an  
20 integrated circuit containing various processing units for implementing the functions of the playback apparatus. The playback apparatus manufactured in the above manner is composed of a BD drive 1, an arrival time clock counter 2, a source de-packetizer 3, a PID filter 4, a transport  
25 buffer 5, a multiplexed buffer 6, a coded picture buffer 7, a video decoder 8, a decoded picture buffer 10, a video plane 11, a transport buffer 12, a coded data buffer 13, a stream graphics processor 14, an object buffer 15, a

composition buffer 16, a composition controller 17, a presentation graphics plane 18, a CLUT unit 19, a transport buffer 20, a coded data buffer 21, a stream graphics processor 22, an object buffer 23, a composition buffer 24, a composition controller 25, an interactive graphics plane 26, a CLUT unit 27, compositors 28 and 29, a switch 30, a network device 31, a local storage 32, an arrival time clock counter 33, a source de-packetizer 34, a PID filter 35, a switch 36, a transport buffer 37, an elementary buffer 38, an audio decoder 39, a transport buffer 40, a buffer 41, a text subtitle decoder 42, a scenario memory 43, a controller 44, and a PSR set 46. Note that the internal structure illustrated in the figure is a decoder model based on the MPEG T-STD model and capable of downconverting.

[0047]

The BD drive 1 loads/ejects the BD-ROM and accesses the BD-ROM to sequentially read Aligned Units each composed of 32 ES-TS packets.

The arrival time clock counter 2 generates an arrival time clock using a 27 MHz crystal oscillator (27 MHz X-tal). The arrival time clock is a clock signal defining the timeline on which the ATS assigned to each TS packet is based.

[0048]

Once an Aligned Unit composed of 32 EX-TS packets is read from the BD-ROM, the source de-packetizer 3 removes the TP\_extra\_header from each ES-TS packet carrying the Aligned Unit and outputs the resulting TS packets to the PID filter 4. The output by the source de-packetizer 3

to the PID filter 4 is performed at the timing when the time measured by the arrival time clock counter 2 reaches the ATS shown by the TP\_extra\_header. Since the output to the PID filter 4 is carried out in accordance with the  
5 ATSS, the TS packets are sequentially output to the PID filter 4 in accordance with the current time measured by the arrival time clock counter 2, irrespective of the speed at which data is read from the BD-ROM, such as 1x-speed or 2x-speed.

10 [0049]

The PID filter 4 judges, with reference to the PID attached to the TS packets, the type of stream to which the TS packets belong is a video stream, a PG stream, or an IG stream. According to the judgment, the PID filter  
15 4 outputs the TS packets to one of the transport buffers 5, 12, 20, and 37.

The transport buffer (TB) 5 is a buffer for temporarily storing TS packets output from the PID filter 4, if the TS packets belong to a video stream.

20 [0050]

The multiplexed buffer (MB) 6 is a buffer for temporarily storing PES packets output from the transport buffer 5, in order to later output the video stream to the coded picture buffer 7.

25 The coded picture buffer (CPB) 7 is a buffer for storing coded pictures (I pictures, B pictures, and P pictures).  
[0051]

The video decoder 8 decodes individual frames contained

in the video elementary stream at every predetermined decoding time (DTS) to obtain a plurality of frames and writes the resulting picture data on the decoded picture buffer 10.

5       The decoded picture buffer 10 is a buffer on which decoded picture data is written.

          The video plane 11 is used for storing uncompressed picture data. A plane is a memory area of the playback apparatus for storing a frame of pixel value data. The  
10       video plane 11 stores picture data at the resolution of  $1920 \times 1080$ , and the picture data is composed of pixel values each expressed by 16-bit YUV values.

[0052]

          The transport buffer (TB) 12 is a buffer for temporarily  
15       storing TS packets output from the PID filter 4, if the TS packets belong to a PG stream.

          The coded data buffer (CDB) 13 temporarily stores PES packets constituting a PG stream.

          The stream graphics processor (SPG) 14 decodes PES  
20       packets carrying graphics data (ODSs) to obtain uncompressed bitmap data expressed by index colors, and writes the obtained graphics data as a graphics object on the object buffer 15.

[0053]

25       The object buffer 15 holds the graphics object obtained as a result of the decoding by the stream graphics processor 14.

          The composition buffer 16 is memory for storing control



information (PCS) used for graphics data rendering.

The composition controller 17 analyzes the PCS stored on the composition buffer 16 and executes control according to the analytical result.

5 [0054]

The presentation graphic plane 18 is a memory area as large as one full screen and stores uncompressed graphics data worth one screen. The presentation graphic plane 18 stores uncompressed graphics data at the resolution of 1920  
10 × 1080 and the uncompressed graphics data is composed of pixel values each expressed using 8-bit index colors. By converting the index colors with reference to a CLUT (Color Lookup Table), the uncompressed graphics data stored on the presentation graphics plane 18 is supplied for display.

15 [0055]

The CLUT unit 19 converts the index colors of the uncompressed graphics data stored on the presentation graphic plane 18 to Y, CR, and Cb values.

The transport buffer (TB) 20 is a buffer for temporarily  
20 storing TS packets belonging to an IG stream.

The coded data buffer (CDB) 21 is a buffer for temporarily storing PES packets constituting an IG stream.

[0056]

The stream graphics processor (SPG) 22 decodes PES  
25 packets containing graphics data and writes uncompressed graphics data obtained by the decoding to the object buffer 23.

The object buffer 23 stores a plurality of uncompressed

graphics objects decoded by the stream graphics processor  
22.

[0057]

The composition buffer 24 is a buffer for storing  
5 control information used for graphics data rendering.

The composition Controller 25 analyzes the control  
information stored on the composition buffer 24 and executes  
control according to the analytical result.

The interactive graphics plane 26 is a plane on which  
10 uncompressed graphics data obtained as a result of the  
decoding by the stream graphics processor (SGP) 22 is written  
at the resolution of  $1920 \times 1080$ . The graphics data is  
composed of pixel values each expressed using 8-bit index  
colors. By converting the index colors with reference to  
15 the CLUT (Color Lookup Table), the uncompressed graphics  
data stored on the interactive graphics plane 26 is supplied  
for presentation.

[0058]

The CLUT unit 27 converts the index colors of the  
20 uncompressed graphics data stored on the interactive  
graphics plane 26 to Y, CR, and Cb values.

The compositor 28 overlays the uncompressed frame data  
stored on the video plane 11 with the uncompressed graphics  
object stored on the presentation graphic plane 18. As  
25 a result of the overlaying, the intermediate composite image  
in which text subtitles are overlaid on video is obtained.

[0059]

The compositor 29 overlays the uncompressed graphics

object stored on the interactive graphics plane 26 with the intermediate composite image (uncompressed picture data overlaid with the uncompressed graphics object rendered on the presentation graphic plane 18) output from the compositor 28.

The switch 30 selectively supplies to, the transport buffer 20, the TS packets read from the BD-ROM or the TS packets read from the local storage 32.

[0060]

The network device 31 is used to implement the communications functionality of the playback apparatus. More specifically, the network device 31 establishes TCP connection, FTF connection, and so on with a web site at an URL.

The local storage 32 is a hard disk used for storing contents supplied from a various recording media and communications media. Contents downloaded from the web site via the connection established by the network device 31 are also stored to the local storage 32.

[0061]

The source de-packetizer 34 removes the TP\_extra\_header from each TS packet constituting the AV clip read from the local storage 32 and outputs the TS packets without headers to the PID filter 35. The output of the TS packets to the PID filter 35 is carried out at the timing when the time measured by the arrival time clock counter 33 reaches the ATS shown by the TP\_extra\_header.

[0062]

The PID filter 35 switches to output the TS packets read from the local storage 32 to either of the PG stream decoder, IG stream decoder, and the audio decoder.

The switch 36 supplies to the audio decoder 39 the  
5 TS packets read from the BD-ROM or from the local storage 32.

The transport buffer (TB) 37 is used to store TS packets carrying an audio stream.

[0063]

10 The elementary buffer (EB) 38 is used to store the PES packets carrying the audio stream.

The audio decoder 39 decodes the PES packets output from the elementary buffer 38 and outputs uncompressed audio data.

15 The transport buffer (TB) 40 is used to store TS packets carrying a text subtitle stream.

[0064]

The elementary buffer (EB) 41 is used to store PES packets carrying the text subtitle stream.

20 The text subtitle decoder 42 decodes PES packets read to the elementary buffer 41 and supplies the resulting data for presentation. To decode the text subtitle stream, the text subtitle decoder 42 expands text strings contained in the text subtitle stream into bitmapped data, by applying  
25 font data separately read from the local storage 32. The resulting data is written on the presentation graphics plane 18.

[0065]

The scenario memory 43 is used to store current PlayList information and current Clip information. The current PlayList information used herein refers to the currently processed PlayList information from among a plurality of  
5 pieces of PlayList information stored on the BD-ROM. The current Clip information used herein refers to the currently processed Clip information from among a plurality of pieces of Clip information stored on the BD-ROM.

The controller 44 is composed of an instruction ROM  
10 and a CPU. The controller 44 executes software stored on the instruction ROM to carry out overall control of the playback apparatus. The control executed on the playback apparatus dynamically changes in response to a user event generated upon receipt of a user operation and in accordance  
15 with the values held in each PSR of the PSR set 49.

[0066]

The PSR set 46 is a set of non-volatile registers provided within the playback apparatus. The set of registers include 64 player status registers  
20 (PSR(1)-PSR(64)) and 4,096 general-purpose registers (GPRs). The 64 player status registers (PSRs) each represent the current status of the playback apparatus, such as the current playback point. Among the 64 PSRs, the values of PSR(5)-PSR(8) represent the current playback  
25 point. Specifically, PSR(5) is set to a value from 1-999 to indicate the chapter number to which the current playback point belongs. When set to "0xFFFF", PSR(5) indicates that the chapter numbers are invalid in the playback apparatus.

[0067]

PSR(6) is set to a value from 0-999 to indicate the PL number to which the current playback point belongs (current PL Number).

5 PSR(7) is set to a value from 0-255 to indicate the PlayItem number to which the current playback point belongs (current PI Number).

PSR(8) is set to a value from 0-0xFFFFFFFF and indicates the current playback point (current PTM) in 45 kHz accuracy.

10 [0068]

This concludes the description of the internal structure of the playback apparatus. Among the components of the playback apparatus, the videodecoder 8 and the decoded picture buffer 10 are of significant importance. Thus,  
15 a more detailed description thereof will be given with reference to Figs. 19-21.

The decoded picture buffer 10 is used to store a plurality of decoded pictures. Fig. 19 illustrates the internal structure of the decoded picture buffer 10. As  
20 illustrated in the figure, the decoded picture buffer 10 stores decoded pictures including reference pictures and non-reference pictures. The reference pictures include short-term reference pictures and long-term reference pictures. The short-term reference pictures are stored  
25 to a FIFO memory area and handled in the first-in, first-out (FIFO) method. On the other hand, long-term reference pictures are not stored to the FIFO memory area and not handled in the FIFO method.

[0069]

Fig. 20 illustrates the decoding process of a Non-IDR I picture by the video decoder 8. During the decoding process of a Non-IDR I picture, references are made to the long-term reference pictures and the short-term reference pictures stored on the decoded picture buffer 10. Arrows *rf1*, *rf2*, and *rf3* illustrated in the figure schematically represent references to the short-term reference pictures, whereas arrows *rf4*, *rf5*, and *rf6* schematically represent references to long-term reference pictures. Fig. 21 illustrates the contents stored in the decoded picture buffer 10 at the time of the IDR picture decoding. At the time of decoding the IDR picture, the video decoder 8 and the decoded picture buffer 10 are instantaneously refreshed, so that all the short-term and long-term reference pictures stored on the decoded picture buffer 10 are erased. This concludes the details of the coded picture buffer 7, the video decoder 8, and the decoded picture buffer 10. Next, the following describes the processing steps performed by the controller 44.

[0070]

The controller 44 controls the BD drive 1 and the video decoder 8 so as to execute fast-speed playback or jump playback of an MPEG4-AVC video stream.

The fast-speed playback is executed by sequentially playing back, out of a plurality of pictures contained in the video stream, I pictures (including IDR pictures and Non-IDR I pictures). Here, the EP\_map shows entry points

each along with the position and the size of an IDR or Non-IDR I picture. Thus, by selectively reading and playing back I pictures contained in the video stream, the playback apparatus can execute trick play of the video stream at, for example, a double- or triple-speed.

[0071]

There are two types of jump playback: one is time-search playback and the other is PL playback. The time-search playback is executed upon receipt of timing information from a user and playback of a video stream is started from a playback point corresponding to a specific time and second indicated in the timing information. At the time of executing the jump playback, the controller 44 converts the timing information into the address of an I picture stored on the BD-ROM. Then, the controller 44 causes the BD-ROM to be read starting from the TS packet at the thus obtained I picture address and causes the read TS packets to be sequentially supplied to the decoder.

[0072]

The PL playback refers to playback of a section of a video stream between points corresponding to In\_time and Out\_time indicated in PlayList information.

The principal part of the above-mentioned playback control is a process of deriving an I picture address from timing information. Fig. 22 is a flowchart of a process of converting timing information into an I picture address. In the flowchart, the timing information denoted as In\_time specifies a jump playback point to be accessed to execute



jump playback. In a step S1 illustrated in Fig. 22, the value of In\_time is assigned to PTS\_EP\_start. A step S2 is to calculate a pair of EP\_High\_id and EP\_Low\_id values indicating an entry point that is near the PTS\_EP\_start .

5 More specifically, the EP\_High\_id to be calculated is an identifier specifying a nearby EP\_High preceding the In\_time. On the other hand, the EP\_Low\_id is an identifier specifying an EP\_Low indicating a nearby temporal point following the EP\_High [EP\_High\_id] and preceding the  
10 In\_time.

[0073]

In order to calculate the value of EP\_High\_id, the controller 44 keeps adding the time length of each PTS\_EP\_High included in a plurality of EP\_High values until  
15 the total  $\Sigma$  of the time lengths first exceeds the In\_time. The time length indicated by each PTS\_EP\_High is a time unit whose most significant bits are held by the PTS\_EP\_High. The controller 44 then identifies the  $k$ -th EP\_High\_id that results in the total  $\Sigma$  first exceeding the In\_time and  
20 determines the value obtained by  $(k - 1)$  as the value of EP\_High\_id.

[0074]

Similarly, to calculate the value of EP\_Low\_id, the controller 44 keeps adding, to the total  $\Sigma$  of up to the  
25 PTS\_EP\_High (EP\_High\_id), the time length indicated by each PTS\_EP\_Low included in EP\_Low, until the resulting total first exceeds In\_time. The controller 44 then identifies the  $h$ -th EP\_Low\_id that causes the resulting total to first

exceeds the In\_time, and determines the value obtained by  
(h - 1) as the value of EP\_Low\_id.

[0075]

The pair of EP\_High\_id and EP\_Low\_id values specifies  
5 a nearest entry point preceding the In\_time.

Once the EP\_Low\_id value is obtained, the controller  
44 enters a loop composed of steps S3-S5. More specifically,  
the controller 44 assigns the EP\_Low\_id value to a variable  
j (step S3) and executes the loop composed of the steps  
10 S4 and S5. In each iteration of the loop, the variable  
j is decremented by "1" (step S4) and a judgment is made  
as to whether the is\_angle\_change\_point  
(PTS\_EP\_Low[j].is\_angle\_change\_point) is set to the value  
"1" (step S5). The loop is repeatedly executed until the  
15 judgment in the step S5 results in YES, i.e. as long as  
the is\_angle\_change\_point field of each entry point is set  
to "0".

[0076]

That is, the loop is terminated if the entry point  
20 specified by the variable j has the is\_angle\_change\_point  
set to the value "1". When the judgment in the step S5  
results in YES, the controller 44 assigns the value of  
variable j to the EP\_Low\_id (step S6) and calculates the  
EP\_High[i] having the ref\_to\_EP\_Low\_id[i] that specifies  
25 an entry point near the EP\_Low\_id (step S7). Once the values  
of the EP\_Low\_id and the variable i are calculated, the  
controller 44 calculates the SPN\_EP\_Start using the  
SPN\_EP\_Low[EP\_Low\_id] and SPN\_EP\_High[i] values (step S8).

Finally, the thus calculated SPN\_EP\_start value is converted into an I picture address (step S9).

[0077]

An SPN is a serial number assigned to an individual  
5 TS packet. In order to read a TS packet having a specific  
SPN, the SPN needs to be converted into a relative sector  
number. As illustrated in Fig. 4, TS packets are converted  
into Aligned Units each containing 32 TS packets, and each  
Aligned Unit is recorded in three sectors. Thus, by  
10 dividing the SPN by 32, the number of the Aligned Unit  
containing the I picture is calculated. Then, by  
multiplying the Aligned Unit number by 3, the sector address  
of the Aligned Unit located near the SPN is calculated.  
The sector address calculated in the above manner is a  
15 relative sector number counted from the start of one AV  
clip. Thus, by setting the file pointer to the relative  
sector number, the playback apparatus reads the AV clip  
to supply the I picture to the video decoder 8.

[0078]

20 Through the above processing, the playback apparatus  
successfully identifies an entry point indicating an IDR  
picture located at a point preceding the In\_time. Reading  
of the IDR picture and the following pictures multiplexed  
in the stream ensures that the decoder is supplied with  
25 all the reference pictures necessary for decoding a picture  
corresponding to the In\_time. This concludes the  
description of processing for deriving the I picture address  
from timing information. Next, a description is given of

the playback processing based on PlayList information.  
[0079]

Fig. 23 is a flowchart of the PL playback performed by the controller 44. In the description regarding this  
5 flowchart, the PlayItem currently subject to the playback processing is denoted as PlayItem #x. According to the flowchart, first, the current PL information (.mpls) is read (step S101), and the steps S102-S110 are performed. The steps S102-S110 create a loop in which the steps S103-S110  
10 are repeated on each piece of PI information included in the current PL information. The processing exits from the loop when the judgment in the step S109 results in "YES". The PlayItem currently subject to the loop is referred to as PlayItem #x (PI #x). When set to be the first PlayItem  
15 in the current PL, PlayItem #x is initialized (step S102). The terminal condition of the loop described above is satisfied when the last PlayItem in the current PL is designated as PlayItem #x (Step S109: YES). If there is another PlayItem following PlayItem #x in the current PL  
20 (Step S109, NO), the next PlayItem is designated as a new PlayItem #x (Step S110).  
[0080]

In the steps S103-S110 repeated in the loop, the following processing is performed. First, Clip  
25 information specified by the Clip\_information\_file\_name included in the PlayItem #x is read to the memory (step S103). The value held in the In\_time of the PlayItem #x is converted into the address *u* of an I picture, using the

EP\_map associated with the current Clip information (step S104). This conversion of In\_time into an I picture address is carried out in accordance with the flowchart illustrated in Fig. 22. In this way, the I picture address *u* indicating the address of an IDR picture is calculated.

[0081]

Next, the value held in the Out\_time of PlayItem #*x* is converted into the address *v* of an I picture, using the EP\_map associated with the current Clip information (step S105). The conversion of the Out\_time into an I picture address is carried out without conducting the processing in the flowchart illustrated in Fig. 22. Rather, the conversion is carried out in the following way. First, the address of an I picture located at a temporal point near the Out\_time is designated as the address *v*. Next, the address of the first I picture subsequent to the address *v* is obtained, and the address immediately preceding the thus obtained address is designated as an address *w* (Step S107). Finally, the controller 44 instructs the BD-ROM drive 1 to read TS packets starting from the I picture address *u* and ending at the address *w* (step S108).

[0082]

On the other hand, the controller 44 instructs the video decoder 8 to output pictures starting from a point corresponding to the mark\_time\_stamp included in the current PlaylistMark and ending at a point corresponding to the Out\_time of PlayItem #*x* (step S106). Through the above steps S105-S108, playback of part of the AV clip used

by PlayItem #x is executed.

Then, it is judged whether PlayItem #x is the last PI in the current PlayList (step S109).

[0083]

5        If PlayItem #x is not the last PI in the current PlayList, the next PlayItem in the current PlayList is designated as a new PlayItem #x (Step S110) and the processing returns to the step S103. By repeatedly performing the steps S103-S110 described above, the playback apparatus  
10        sequentially plays back PlayItems constituting the PlayList.

As described above, according to the present embodiment, as long as the playback apparatus reads pictures up to entry point specified by the *is\_angle\_change\_point* set to the  
15        value "1", it is ensured that an IDR picture is supplied to the video decoder 8. That is, all the reference pictures necessary for decoding to execute jump playback is made available in the decoded picture buffer 10. Thus, the number of pictures that needs to be read to execute jump  
20        playback is kept to a minimum.

[0084]

As above, even if a video stream is compressed to have IDR pictures at relatively long intervals such as fifteen minutes or thirty minutes of playback time for the sake  
25        of high-compression rate, trick play is efficiently executed. That is, without significantly sacrificing the advantage of high-compression rate achieved by the MPEG4-AVC standard, the playback apparatus is enabled to

efficiently execute trick play.

(SECOND EMBODIMENT)

5 The first embodiment discloses the data structure of the EP\_map containing the *is\_angle\_change\_point* field that indicates a point where the playback apparatus can enter to the AV clip. A second embodiment of the present invention describes an angle change executed by the playback apparatus with the use of angle changeable points indicated by the  
10 *is\_angle\_change\_point*. As described in the first embodiment, the processing of angle change is composed of "exiting" from the currently executed AV clip and "entering" into another AV clip.

[0085]

15 Suppose, for example, the BD-ROM stores a plurality of AV clips containing video images of the same subject shot from different camera angles, for example, the front, right, and left. During playback of the AV clip containing images shot from the front, the playback apparatus may "exit"  
20 from the current AV clip and "enter" to the AV clip containing images shot from the right. As a result, the playback angles are changed from the front to the right. Since the playback images are changed as if a camera angle is changed, the above processing composed of "exiting" from an AV clip  
25 and "entering" to another AV clip is referred to as "angle change". In order to implement the "angle change" functionality, some improvements need to be made on AV clips and PlayList information. The improvement is embodied in

the structure called a multiangle section defined by  
PlayList information containing PlayItem information and  
using a plurality of AV clips.

[0086]

5        Fig. 24 illustrates an application layer layout  
implementing a multiangle section. In the present  
embodiment, a multiangle section contains four angles.  
Thus, the multiangle section is composed of four AV clips  
(00001.m2ts, 00002.m2ts, 00003.m2ts, and 00004.m2ts), one  
10    piece of PlayList information (00001.mpls), and four pieces  
of Clip information (00001.clpi, 00002.clpi, 00003.clpi,  
and 00004.clpi).

[0087]

15        Fig. 25 illustrates the data structure of PlayList  
information. As illustrated in the figure, each piece of  
PlayItem information constituting the multiangle section  
includes two portions: one is a portion compatible with  
a non-multiangle PlayItem and the other is an extended  
portion used for implementing a multiangle section. The  
20    compatible portion is identical in data structure to the  
PlayItem information illustrated in Fig. 16. More  
specifically, the compatible portion is composed of  
"Clip\_information\_file\_name", "Clip\_codec\_identifier",  
"In\_time", and "Out\_time". The AV clip specified in the  
25    compatible portion constitutes the first angle section in  
the multiangle section. With this structure, a playback  
apparatus not capable of handling a multiangle section (a  
playback apparatus capable of handing BD-RE data structure



only) is enabled to read PlayItem information containing multiple angles and duly execute playback of the first angle section by simply manipulating the compatible portion. The extended portion is composed of the following fields:

5 "is\_multi\_angles"; "number\_of\_angles";  
"is\_seamless\_angle\_change"; and "Angle information[2],  
[3] ...[j]".  
[0088]

The "is\_multi\_angles" field indicates whether the  
10 playback section used by this PlayItem is a multiangle section or non-multiangle section.

The "number\_of\_angles" field indicates the number of angles contained in the multiangle section, if the "is\_multi\_angles" field is set to the value indicating a  
15 multiangle section.

The "is\_seamless\_angle\_change" field indicates whether the multi-angle section is prepared for seamless angle change. Whether or not the angle change is to be seamless is determined depending on whether the AV clip  
20 is interleaved or not. In the case of an AV clip that is interleaved, the "is\_seamless\_angle\_change" is set to "ON". On the other hand, in the case of an AV clip that is not interleaved, the "is\_seamless\_angle\_change" is set to "OFF".

25 [0089]

Each piece of "Angle info [2]-[j]" relates to an individual angle section contained in the multiangle section and includes the following fields:

"Clip\_Information\_file\_name" and  
"Clip\_codec\_identifier".

The "Clip\_Information\_file\_name [angle\_id]" field  
indicates the file name containing an AV clip used in the  
5 angle section.

The "Clip\_codec\_identifier [angle\_id]" field  
indicates the codec of the AV clip contained in the file  
specified by the Clip\_Information\_file\_name field.  
[0090]

10 As described above, the "Angle info" contains neither  
"In\_time" nor "Out\_time". It is because the In\_time and  
Out\_time included in the compatible portion collectively  
specify the start and end points of each of the second and  
the following angle sections. That is to say, every AV  
15 clips specified by the Clip\_Information\_file\_name contained  
in a respective piece of Angle information in the extended  
portion needs to have the same playback time with the AV  
clip specified by the Clip\_Information\_file\_name in the  
compatible portion. In addition, the timestamps (System  
20 Time Clock) specifying the playback timing of the respective  
AV clips on the playback timeline need to be the exactly  
same value.

[0091]

Both the compatible and extended portions of PlayItem  
25 information have the Clip\_Information\_file\_name field.  
Thus, a playback section of each of a plurality of AV clips  
is specified all at once.

Fig. 26A illustrates the playback sections of a

plurality of AV clips collectively specified by the four  
Clip\_Information\_file\_name fields contained in the  
PlayItem information. In the figure, the first level  
illustrates four timelines of the four AV clips (AV clips  
5 #1, #2, #3, and #4). The fifth level illustrates the PL  
timeline. The four Clip\_Information\_file\_name fields  
included in the PlayItem information specify the four  
timelines. With this data structure, the In\_time and  
Out\_time of the PlayItem define four playback sections that  
10 are selectable for playback. That is, a section composed  
of a plurality of selectable angle images (so-called a  
multiangle section) is defined on the PL timeline. The  
four playback sections of the four AV clips specified by  
the In\_time and the Out\_time are located at the same position  
15 on the PlayList timeline.  
[0092]

The following describes how the AV clips used to  
constitute a multiangle section is divided on a BD-ROM.  
Each AV clip is stored on the BD-ROM in units called extents.  
20 An extent is one divided portion that is recorded in a  
contiguous area on the BD-ROM and is also referred to as  
a "segment".

Suppose, for example, AV clips #1-#4 illustrated in  
Fig. 24 contain video data of motion picture images shot  
25 from four different angles. In this case, each of AV clips  
#1-#4 are divided into five extents as follows:

AV clip #1 →

AV clip #1.1/5, AV clip #1.2/5, AV clip #1.3/5, AV

clip #1.4/5, and AV clip #1.5/5.

AV clip #2 →

AV clip #2.1/5, AV clip #2.2/5, AV clip #2.3/5, AV clip #2.4/5, and AV clip #2.5/5

5 AV clip #3 →

AV clip #3.1/5, AV clip #3.2/5, AV clip #3.3/5, AV clip #3.4/5, and AV clip #3.5/5

AV clip #4 →

10 AV clip #4.1/5, AV clip #4.2/5, AV clip #4.3/5, AV clip #4.4/5, and AV clip #4.5/5

Fig. 26B illustrates the extents of each AV clip on the PlayList timeline. The five extents of each AV clip are located at the same positions on the playback timeline with the counterpart extents of the other AV clips. More specifically, AV clip #1.1/5, AV clip #2.1/5, AV clip #3.1/5, and AV clip #4.1/5 are all located at the same position on the timeline. Likewise, AV clip #1.2/5, AV clip #2.2/5, AV clip #3.2/5, and AV clip #4.2/5 are all located at the same position on the timeline. AV clip #1.3/5, AV clip #2.3/5, AV clip #3.3/5, and AV clip #4.3/5 are all located at the same position on the timeline.

[0093]

The extents of the four AV clips are recorded onto the BD-ROM by interleaving. Interleaving is a technique of recording multiple files, so that each file is divided into a plurality of extents and that extents with the same playback timing are alternately recorded on the BD-ROM. Owing to the interleaving, the playback apparatus currently

reading a file can suitably switch to read another file.  
Thus, the playback apparatus is enabled to "exit" from the  
currently played AV clip and "enter" into another AV clip  
without interrupting playback, thereby to execute seamless  
5 angle change.

[0094]

The extents illustrated in Fig. 26B are interleaved  
on the BD-ROM as illustrated on Fig. 27A.

Fig. 27A is an allocation image showing the arrangement  
10 of the four AV clips constituting the multiangle section  
on the BD-ROM. As described above, each of the four AV  
clips is divided into five extents. The first extents of  
the respective AV clips (AV clip #1.1/5, AV clip #2.1/5,  
AV clip #3.1/5, and AV clip #4.1/5) are contiguously recorded.

15 Those extents AV clip #1.1/5- AV clip #5.1/5 are all part  
of the AV clips to be played back in the same playback period.  
That is, all the extents corresponding to the same playback  
period are collectively and contiguously recorded on the  
BD-ROM. The extents of AV clip #1 and of AV clip #2 are  
20 arranged in series on the BD-ROM. Thus, by reading AV clip  
#1.1/5 together with AV clip #2.1/5, either of AV clip #1.1/5  
and AV clip #2.1/5 can be selectively decoded. This makes  
it possible to implement angle change in response to a user  
operation.

25 [0095]

The multiangle section of an AV clip is divided into  
a plurality of portions at boundaries residing on points  
of "entering" and "exiting" described in the first

embodiment. That is, the start and end points of each divided portion coincide with an entering point and an exit point. Since a plurality of divided portions each start with an entering point and ends with an exit point are  
5 linearly arranged, entering points and exit points alternate. This arrangement helps the playback apparatus to suitably exit from an AV clip and enter into another AV clip.

[0096]

10 Fig. 27B illustrates the internal structure of one extent of an AV clip. As illustrated in the figure, the first NAL unit (or the first piece of video data) contains an Access Unit Delimiter (AUD) followed by an IDR picture, which is an independently decodable Access Unit. The PTS  
15 and SPN of the IDR picture are specified by the entry point having the *is\_angle\_change\_point* field set to the value "1". No extent should be shorter than a predetermined length for the following reason. When read from the BD-ROM, an extent shorter than the predetermined length may cause  
20 the buffer to underflow.

[0097]

One extent may have more than one IDR pictures, each of which serves as an entering point. Yet, the length of the extent between the last IDR picture and the end of the  
25 extent should not be shorter than the predetermined length mentioned above. Fig. 28 illustrates the concept of how to determine the contiguous length to the extent. In the figure, entry points #1-#5 have the *is\_angle\_change\_point*

fields set to the values "1", "0", "1", "0", and "1" in the stated order. Thus, the length from entry point #5 to the end of the extent should not be shorter than the predetermined length.

5 [0098]

Fig. 29 illustrates the allocation of the extents on the BD-ROM, along with the entry point setting. In the figure, the shaded portions represent the Access Unit Delimiter of an I picture (IDR picture or Non-IDR I picture) located at the start of each extent constituting AV clip #2. Note that the I pictures (IDR pictures or Non-IDR I pictures) located at the start of AV clips #3, #4, and #5 are not illustrated for the sake of simplicity in the illustration. In the case where the extents constituting AV clip #2 (AV clip #2.1/5, AV clip #2.2/5, AV clip #2.3/5, AV clip #2.4/5, and AV clip #2.5/5) are interleaved with the extents of another AV clip, the EP\_map contained in the Clip information associated with AV clip #2 is set to indicate the five entry points #1, #2, #3, #4, and #5. Entry points #1, #2, #3, #4, and #5 are indicated in correspondence with the SPN and PTS values of a corresponding one of AV clip #2.1/5, AV clip #2.2/5, AV clip #2.3/5, AV clip #2.4/5, and AV clip #2.5/5.

[0099]

25 Suppose, for example, among the five extents of AV clip #2, the first pictures in AV clip #2.2/5, AV clip #2.4/5, AV clip #2.5/5 are Non-IDR I pictures, whereas the first pictures in AV clip #2.1/5 and AV clip #2.3/5 are IDR pictures.

In that case, the *is\_angle\_change\_point* is set to the value "1" for each entry point #1 and #3, which correspond to the SPNs of AV clip #2.1/5 and AV clip #2.3/5, respectively.

As described above, the start of each extent of AV clip #2 is indicated by entry points whose *is\_angle\_change\_point* is set to the value "1". With this setting, the start point of such an extent is regarded as an entering point, which is a point at which the playback apparatus can enter into the AV clip. Since the end point of an extent immediately precedes an extent with "*is\_angle\_change\_point*" set to the value "1", the endpoint is regarded as an exit point, which is a point at which the playback apparatus can exit from the AV clip. Fig. 29 illustrates the entry points set on the extents of AV clip #2. Similarly to the extents of AV clip #2, the start point of each extent of AV clips #1, #3, #4, and #5 is indicated by an entry point with the *is\_angle\_change\_point* set to the value "1". Since the playback apparatus is enabled to exit from, and enter into AV clips #1, #2, #3, #4, #5 at a boundary between the end point of an extent and the start point of another extent, seamless angle change is guaranteed.

[0100]

This concludes the description of the improvement made on the recording medium according to the present embodiment. Next, a description of an improvement made on the playback apparatus will be given. According to the second embodiment, the playback apparatus indicates an angle section with



PSR(3) included in the PSR set 46. PSR(3) is used to store a value indicating the current angle. The controller 44 of the playback apparatus according to the second embodiment causes the angle section to be selected for playback, in accordance with the value held in PSR(3).

[0101]

Fig. 30 illustrates the valid values of PSR(3) and the relationship with PlayItem and Clip information. The leftmost block of the figure illustrates the values (1-4) of PSR(3).

When PSR(3) is set to the value "1", the playback apparatus reads the Clip information specified by the Clip\_information\_file\_name in the compatible portion of the PlayItem information. As a result, the Clip information contained in the file called "00001.clpi" is read to the memory. The playback apparatus then refers to the entry\_map contained in the read Clip information and executes playback of the AV clip (00001.m2ts).

[0102]

Similarly, when PSR(3) is set to the value "2", the playback apparatus reads the Clip information specified by the Clip\_information\_file\_name in Angle information[2] of the PlayItem information. As a result, the Clip information contained in the file called "00002.clpi" is read to the memory. The playback apparatus then refers to the entry\_map contained in the read Clip information and executes playback of the AV clip (00002.m2ts).

When PSR(3) is set to the value "3", the playback

apparatus reads the Clip information specified by the Clip\_information\_file\_name in Angle information[3] of the PlayItem information. As a result, the Clip information contained in the file called "00003.clpi" is read to the  
5 memory. The playback apparatus then refers to the entry\_map contained in the read Clip information and therefore executes playback of the AV clip (00003.m2ts).

[0103]

When PSR(3) is set to the value "4", the playback  
10 apparatus reads the Clip information specified by the Clip\_information\_file\_name in Angle information[4] of the PlayItem information. Thus, the Clip information contained in the file called "00004.clpi" is read to the memory. The playback apparatus then refers to the entry\_map  
15 contained in the read Clip information and therefore executes playback of the AV clip (00004.m2ts).

The following describes the processing steps performed by the controller 44 in accordance with the PlayItem information illustrated in Fig. 25. Fig. 31 is a flowchart  
20 of processing steps performed to execute of PlayList playback according to the second embodiment.

[0104]

This flowchart is basically identical to the flowchart illustrated in Fig. 23, except for that the step S103 is  
25 replaced with steps S111-S114. More specifically, in order to execute playback of one of PlayItems contained in the current PlayList information, the controller 44 assigns the value held in PSR(3) to a variable V (step S111) and

judges whether the variable V is greater than or equal to "2" (step S112). If the variable V is equal to "1" (step S112: NO), the Clip information specified by the Clip\_information\_file\_name in the compatible portion of the PlayItem is read to the memory (step S113). Then, the controller 44 controls the BD-ROM drive 1 to read a sequence of TS packets from the point corresponding to the In\_time to the point corresponding to the Out\_time of PlayItem #x (steps S104-S108).

10 [0105]

If the variable V is greater than or equal to "2" (step S112: YES), the Clip information specified by the Clip\_information\_file\_name in the Angle information[V] of PlayItem #x is read to the memory (step S114). Then, the controller 44 controls the BD-ROM drive 1 to read a sequence of TS packets from the point corresponding to the In\_time to the point corresponding to the Out\_time of PlayItem #x (steps S104-S108).

As described above, by accessing a different AV clip in accordance with the value of PSR(3), the playback apparatus executes playback of a requested angle section.  
[0106]

Fig. 32 is a flowchart of processing steps performed to read a multiangle section from a disc. In the following description relating to the figure, the term "current address" refers to an address of a point on a disc currently read by the optical pickup. The term "current extent" refers to the extent containing the current address. The

term "current angle" refers to a currently played angle contained in the multiangle section.

[0107]

The steps S50-S52 constitute a main loop of the  
5 flowchart. In each iteration of the loop, the current address is updated to the next address (step S50).

By repeating the steps S50-S52, the current address is successively updated to the next address within one extent.

10 [0108]

In the step S51, it is judged whether an angle change is requested. An angle change is requested at a push of an angle key or numeric key on the remote controller. If an angle change is requested, the value indicating the  
15 requested angle is assigned to the variable V (step S53) and the preparation flag is set to the value "1" (step S54).

Here, if the angle change is requested at a push of the angle key, the value obtained by adding "1" to the PSR(3) value is assigned to the variable V. On the other hand,  
20 if the angle change is requested at a push of a numeric key, the value corresponding to the numeric key is assigned to the variable V.

[0109]

In the step S52, it is judged whether the current address  
25 has reached the end address of the current extent. The judgment in the step S52 results in "YES" when all the TS packets of the current extents are read and thus the current address reaches the end point of the extent.

If the judgment in the step S52 results in "YES", the steps S55-S57 are performed. In the step S55, it is judged whether the preparation flag is set to the value "1". If the preparation flag = "0", the next extent in the current  
5 AV clip is set as a new current extent (step S56), and the address of the first Access Unit Delimiter in the new current extent is set to be a new current address (step S57). Then the loop composed of the steps S50-S52 is performed again. That is, as long as the preparation flag is equal to "0",  
10 the next extent in the current angle is read.  
[0110]

On the other hand, if the preparation flag is set to the value "1", the AV clip to be read is switched as follows. This is because the AV clip of the requested angle is started  
15 to be read at the timing when the current address reaches the end of the current extent.

In order to switch the AV clips to be read, first of all, among the extents of the requested angle section, the extent that immediately follows the current extent in the  
20 presentation order is designated as an extent *dst* (step S58). Then, the Eptop indicating the first Access Unit Delimiter in the extent *dst* is identified (step S59). Then, it is judged whether the *is\_angle\_change\_point* of the Eptop is set to the value "1" (step S60). This judgment is made  
25 to see whether the start point of the extent *dst* is a point where the playback apparatus can enter to the AV clip. If the *is\_angle\_change\_point* is set to the value "0", the step S56 is performed with the preparation flag maintained to

the value "1". Through the steps S56-S57, the next extent in the current angle is read, and playback of the current angle is continued. In other words, playback of the current angle is continued as long as the extent *dst* is in condition  
5 where the point *is\_angle\_change\_point* is not set to the value "1", i.e. as long as the extent *dst* is not a point where the playback apparatus can enter to the AV clip.  
[0111]

If the *is\_angle\_change\_point* is set to the value "1",  
10 the extent *dst* is designated as a new current extent (step S61), and the address of the first Access Unit Delimiter in the extent *dst* is set as a new current address (step S62). Then, the preparation flag is cleared to "0", and PSR(3) is set to the variable *V* indicating the requested  
15 angle (step S63). Then, the processing returns to the step S113. As a result, Clip information specified by the *Clip\_information\_file\_name* corresponding to the variable *V* is read and playback is continued in accordance with the thus read Clip information.  
20 [0112]

Fig. 33 illustrates a process of reading the BD-ROM for executing playback of an angle image A. As illustrated in the figure, five extents (AV clip #1.1/5, AV clip #1.2/5, AV clip #1.3/5, AV clip #1.4/5, and AV clip #1.5/5) of AV  
25 clip #1 are sequentially read.

Fig. 34 illustrates a process of reading the BD-ROM performed upon receipt of a user operation of requesting an angle change. As illustrated in the figure, a user

operation requesting an angle change is received during the time AV clip #1.2/5 of AV clip #1 is being read (step S5: YES). In response to the user operation, the preparation flag is set to the value "1" (step S54). The user operation received herein is to request an angle change from the angle image presented by AV clip #1 to an angle image presented by AV clip #2. Since the angle change is requested during the time AV clip #1.2/5 is being read, AV clip #2.3/5 is designated as the extent *dst*, which is the extent that immediately follows the current extent in the presentation order (step S58). The start point of the extent *dst* is specified by entry point #3 corresponding to the PTS\_EP\_start indicating the temporal point *t3*. Thus, a reference is made to the *is\_angle\_change\_point* corresponding to entry point #3 of AV clip #2 (step S60): In this case, the *is\_angle\_change\_point* of entry point #3 is set to the value "1". That is to say, entry point #3 is a point where the playback apparatus can enter to the AV clip. Thus, the extent *dst* (i.e. AV clip #2.3/5) is set as a new current extent (step S61), and the address of the first Access Unit Delimiter in the new current extent is set as a new current address (step S62). Then, PSR(3) is set to the value "2" specifying AV clip #2 (step S64). As a result, AV clip #2.3/5, AV clip #2.4/5, AV clip #2.5/5 of AV clip #2 are sequentially read.

[0113]

Fig. 35 illustrates a process of reading the BD-ROM performed upon receipt of a user operation of requesting

an angle change. As illustrated in the figure, a user operation requesting an angle change is received during the time AV clip #1.1/5 of AV clip #1 is being read (step S51: YES). In response to the user operation, the preparation flag is set to the value "1" (step S54). Since the angle change is requested during the time AV clip #1.1/5 is being read, AV clip #2.2/5 is designated as the extent *dst* (step S58). The start point of the extent *dst* is specified by entry point #2 corresponding to the PTS\_EP\_start indicating the temporal point *t2*. Thus, a reference is made to the *is\_angle\_change\_point* corresponding to entry point #2 of AV clip #2 (step S60). In this case, the *is\_angle\_change\_point* of entry point #2 is set to the value "0". That is to say, entry point #2 is not a point where the playback apparatus can enter to the AV clip. Thus, AV clip #1.2/5, which is the extent next to AV clip #1.1/5 in the current AV clip #1, is set as a new current extent (step S56). Then, the address of the start point of the current extent is set as a new current address (step S57). As a result, AV clip #1.2/5 is read.

[0114]

When the current address reaches the end of AV clip #1.2/5 (step S52: YES), it is judged whether the preparation flag is set to the value "1" (step S55). Since the preparation flag is set to the value "1" in this case, the judgment in the step S52 results in "YES". Thus, AV clip #2.3/5 is now designated as the extent *dst* (step S56). The start point of the extent *dst* is specified by entry point



#3 corresponding to the PTS\_EP\_start indicating the temporal point *t3*. Thus, a reference is made to the *is\_angle\_change\_point* of entry point #3 of AV clip #2 (step S60). In this case, the *is\_angle\_change\_point* of entry point #3 is set to the value "1". That is to say, entry point #3 is a point where the playback apparatus can enter to the AV clip. Thus, AV clip #2.3/5 designated as the extent *dst* is set as a new current extent (step S61), and the address of the first Access Unit Delimiter in the current extent is set as a new current address (step S62). Then, PSR(3) is set to the value "2" specifying AV clip #2 (step S64). As a result, AV clip #2.3/5, AV clip #2.4/5, AV clip #2.5/5 of AV clip #2 are sequentially read.

[0115]

As in the example illustrated in Fig. 35, there may be a case where the extent of the requested angle located on the PL timeline immediately after the point of the angle change request is not an entering point. In such a case, playback of the extents presenting the current angle is continued until an angle changeable point is reached.

In addition, an angle change to AV clip #2.3/5 is possible until the playback start of the extent of AV clip #1 (AV clip #1.3/5) that is located at the same point on the PlayList timeline. In other words, once playback of the extent of AV clip #1 (AV clip #1.3/5) is started, an angle change to AV clip #2.3/5 is no longer possible.

[0116]

As described above, according to the present embodiment,

the start point of each of a plurality of extents constituting an AV clip is indicated by an entry point. In addition, with reference to the *is\_angle\_change\_point* field of a respective entry point, the playback apparatus can readily  
5 identify which of such entry points are the points where the playback apparatus can enter to the AV clip of a requested angle image. By supplying to the decoder the IDR picture located at an entering point, the playback apparatus can smoothly execute an angle change even if the video stream  
10 is an MPEG4-AVC stream.

[0117]

(THIRD EMBODIMENT)

The first embodiment relates to the improvement for  
15 efficiently executing jump playback of a video stream including IDR pictures at 15- or 30-minute intervals. In contrast, a third embodiment of the present invention relates to a technique of allowing selection as to which of pictures contained in a video stream is encoded to be  
20 IDR pictures. In other words, the present embodiment allows selection to be made at the time of setting encoding conditions, so that optimal pictures are encoded as IDR pictures. An MPEG4-AVC video stream is encoded with the MPEG4-AVC standard and referenced by PlayList information  
25 via Clip information. The present embodiment allows the selection of IDR pictures in view of this nature of PlayList information.

[0118]

Hereinafter, a description is given of the data structure of PlayList information according to this embodiment. Fig. 36 illustrates the internal structure of PlayList information according to the third embodiment.

5 The PlayList information illustrated in the figure differs from the PlayList information of the second embodiment in that PLMark (PLMark #1-#n) is additionally contained. The selection of IDR pictures is implemented in order to more efficiently execute PL playback of PlayList information  
10 having such a data structure.

[0119]

PLMark information (PLMark()) illustrated in Fig. 36 specifies an arbitrary section on the PL timeline as a chapter point. As leader lines *pm1* in Fig. 36 indicate, the PLMark  
15 information includes the following fields: "ref\_to\_PlayItem\_id" and "mark\_time\_stamp". Fig. 37 illustrates chapters defined by the PLMark information. In the figure, the first level illustrates the AV Clip timeline, whereas the second level illustrates the PL  
20 timeline. An arrows *pk1* and *pk2* represent that two pieces of PLMark information each specify a PlayItem (by ref\_to\_PlayItem\_id) and a point (specified by mark\_time\_stamp). As a result, the PLMark information defines three chapters (Chapter#1, #2, and #3) on the PL  
25 timeline. This concludes the description of the PLMark information.

[0120]

Fig. 38 illustrates pictures of the video stream used

by PlayItem #1 contained in PlayList information, together with the relevant part of the entry\_map setting. Suppose, for example, the In\_time of PlayItem #1 specifies a temporal point  $t_2$  on the timeline. In this case, the picture located at the temporal point  $t_2$  is encoded to be an IDR picture. As a result, at the time of executing PlayList information playback, playback in accordance with PlayList #1 is correctly executed simply by reading pictures starting from the picture located at the In\_time of PlayItem #1.

10 [0121]

Fig. 39 illustrates pictures of the video stream used by PlayItem #2. The picture specified by the In\_time of PlayItem #1 is an IDR picture. Yet, the picture specified by the In\_time of PlayItem #2 may or may not be an IDR picture.

15 That is, except for the first piece of PlayItem information in the PlayList information, it is not necessary that the picture specified by the In\_time of a respective piece of PlayItem information be an IDR picture. Rather, each of such pictures may be encoded as a Non-IDR I picture. It is because the MPEG4-AVC format allows one reference picture to be used over a relatively long term. For example, pictures located between In\_time and Out\_time of PlayItem #2 as well as pictures located between In\_time to Out\_time of PlayItem #3 are encoded using a long-term reference picture located between In\_time to Out\_time of PlayItem #1. As a result, it is not necessary to place an IDR picture at the In\_time of PlayItem #2 or at the In\_time of PlayItem #3. Encoding with the use of long-term reference pictures

advantageously reduces the number of IDR pictures. Thus, an MPEG4-AVC video stream is encoded at a high compression rate. It should be noted, however, that the first PlayItem in the PlayList information has no preceding pictures to be used as reference. Thus, at the time of executing playback starting from the In\_time of the first PlayItem, the decoded picture buffer 10 is supplied with no reference picture. That is, the picture specified by the In\_time of the first PlayItem needs to be encoded as an IDR picture.

10 [0122]

Among a plurality of pictures located between the In\_time and the Out\_time of PlayItem information #2, the picture specified by PLMark #1 needs to be encoded as an IDR picture. Each picture specified by PLMark information is regarded as a chapter point. When chapter search is executed to start jump playback from a picture specified by PLMark information, the decoded picture buffer 10 is supplied with no reference picture. Thus, each I picture specified by PLMark information needs to be an IDR picture.

20 [0123]

Fig. 40 illustrates pictures of the video stream used by PlayItem #3. Similarly to Fig. 39, the picture specified by the In\_time of PlayItem #3 illustrated in Fig. 40 may or may not be an IDR picture. Yet, the picture specified by PLMark #3 needs to be encoded as an IDR picture. As a consequence, PLMark playback can be suitably executed, since no reference picture is used to start playback from the chapter.

[0124]

This concludes the description of the improvement made on the recording medium according to the present embodiment. Next, a description is given of an improvement made on the playback apparatus according to the present embodiment. 5 The processing steps to execute PlayList playback are basically identical to those described in relation to the first embodiment. The PlayList playback is executed by converting the In\_time and the Out\_time indicated in 10 PlayList information to I picture addresses.

Among a plurality of pieces of PlayItem information included in PlayList information, the first piece of PlayItem information has the In\_time specifying an IDR picture. Since such an IDR picture is indicated by an entry 15 point with the *is\_angle\_change\_point* field set to the value "1". Thus, by reading the pictures starting from the point specified by the *SPN\_EP\_start* of the entry point corresponding to the In\_time, the controller 44 can ensure that an IDR picture is supplied to the video decoder 8. 20 In response to that an IDR picture is supplied to the video decoder 8, the decoded picture buffer 10 is cleared.

[0125]

As described above, the playback apparatus according to the present embodiment is not required to search an entry 25 point close to the In\_time. Rather, the playback apparatus of the present embodiment is able to supply an IDR picture to the video decoder 8 simply by reading a point corresponding to the In\_time on the BD-ROM. As a result, PL playback

is executed at a higher speed.

In addition, since PLMark information defines chapters, the playback apparatus according to the present embodiment is able to execute, using PlayList information, a chapter search function and chapter skip function. With the chapter search function, the playback apparatus first specifies PlayItem information referred to by the ref\_to\_PlayItem\_id included in the PLMark information. The playback apparatus then executes jump playback of the AV clip that is used by the thus specified PlayItem information, starting from a point specified by the mark\_time\_stamp included in the PLMark information. To this end, the controller 44 specifies one of a plurality of entry points having the PTS\_EP\_start value close to the mark\_time\_stamp value included in the PLMark information. The controller 44 then causes playback to be started from the I picture address corresponding to the SPN\_EP\_start of the thus specified entry point.

[0126]

With the chapter skip function, the playback apparatus specifies PLMark information defining a chapter that is immediately before or after the chapter containing the current playback point. The playback apparatus then conducts a search of chapters defined by the thus PLMark information. As described above, each picture specified by the mark\_time\_stamp in the PLMark information has been encoded to be an IDR picture. Each entry point with the is\_angle\_change\_point field set to the value "1" has the

PTS\_EP\_start value indicating the playback time of an IDR picture. Thus, by reading the pictures starting from the point specified by the SPN\_EP\_start value of any of such entry points, the playback apparatus can ensure that an  
5 IDR picture is supplied to the video decoder 8.  
[0127]

The following describes the processing steps of executing the chapter search and chapter skip functions, with reference to flowcharts. Fig. 41 is a flowchart of  
10 the processing steps of the chapter search function.

According to the flowchart, first, the playback apparatus is placed in a stand-by mode for a user operation of selecting a chapter on a chapter menu (step S124). Upon receipt of a user operation of selecting a chapter, the  
15 PLMark information defining the selected chapter is designated as current PlayListMark (step S125). In a step S126, the PI specified by the ref\_to\_PlayItem\_id field in the current PlayListMark is designated as PlayItem #x. In a step S127, the Clip information specified by the  
20 Clip\_information\_file\_name of PlayItem #x is read. In a step S128, the mark\_time\_stamp value of the current PlayListMark is converted to the I picture address *u*, using the EP\_map associated with the current Clip information. Here, the picture specified by the mark\_time\_stamp value  
25 of the PLMark information is indicated by an entry point with the *is\_angle\_change\_point* field set to the value "1". That is, the I picture address *u* is the address of an IDR picture.



[0128]

In a step S129, the Out\_time of PlayItem #x is converted into an I picture address v, using the EP\_map associated with the current Clip information. In a step S130, the playback apparatus instructs the decoder to output TS packets starting from the point corresponding to the mark\_time\_stamp value of the current PlayListMark and ending at the point corresponding the Out\_time of PlayItem #x. Through the above steps, the playback apparatus converts the I picture addresses u and v and then goes back the step S107 illustrated in Fig. 23. As a result, TS packets of an AV clip that is different from the currently read AV clip are caused to be read, so that playback is switched to the requested chapter. This concludes the description of the processing steps for executing the chapter search function. Next, a description of processing steps for the chapter skip function will be given. Fig. 42 is a flowchart of the processing steps of the chapter skip function.

[0129]

In a step S131, the playback apparatus is placed into a stand-by mode for a user operation made on a SkipNext key or a SkipBack key provided on the remote controller. Upon receipt of a user operation, a step S132 is performed to judge whether SkipNext key or the SkipBack key is pushed. If the SkipBack key is pushed, the direction flag is set to the value "-1" in a step S133. On the other hand, if the SkipNext key is pushed, the direction flag is set to the value "+1" in a step S134.

[0130]

In a step S135, the value held in the direction flag is added to the current PlayListMark number and the addition result is set as a new current PlayListMark number. In the case where the SkipNext key is pushed in the step S131, the direction flag is set to the value "+1". Thus, the current PlayListMark number is incremented. On the other hand, in the case where the SkipBack key is pushed in the step S131, the direction flag is set to the value "-1". Thus, the current PlayListMark number is decremented. After the PLMark information is set as above, the same processing steps S126-S130 as described in Fig. 41 are performed to read suitable TS packets.

[0131]

Here, the picture specified by the mark\_time\_stamp of the PLMark has been encoded as an IDR picture. Thus, each entry point with the *is\_angle\_change\_point* field set to the value "1" has the PTS\_EP\_start value indicating the presentation time of an IDR picture. By reading the pictures starting from the point specified by the SPN of such an entry point, the playback apparatus can ensure that an IDR picture is duly supplied to the video decoder 8.

[0132]

According to the present embodiment, as described above, an AV clip is encoded so as to insert IDR pictures at the point specified by the In\_time of the first PlayItems in PlayList information and at the chapter points specified by PLMark information. This arrangement eliminates the

need for the playback apparatus to search an IDR picture close to the point specified by In\_time of PlayItem or the chapterpoint defined by PLMark information. Consequently, the PlayList playback is executed at a higher speed.

5

[0133]

(Supplemental Notes)

Needless to say, the foregoing descriptions do not cover all the modes of practicing the present invention.

10 The present invention can be practiced also by any of the following modifications (A), (B), (C), (D), ... etc. It should be noted that the inventions recited in the claims of the present application are broadened or generalized descriptions of the above-described embodiments and their  
15 modifications. The extent of the broadening and generalization reflects the state of the art at the time of filing the present application.

[0134]

(A) According to the above embodiments, a BD-ROM is  
20 described as a recording medium according to the present invention. Yet, it should be noted that the features of a recording medium according to the present invention lie in the EP\_map recorded thereon and these features do not depend on the physical property of the BD-ROM. Any other  
25 recording medium is applicable as long as the recording medium can store the EP\_map. Specific examples of such recording media include: optical discs, such as ROM, DVD-RAM, DVD-RW, DVD-R, DVD+RW, DVD+R, CD-R, and CD-RW; and

magneto-optical disks, such as PD and MO. The examples of the recording medium according to the present invention further include semiconductor memory cards, such as CompactFlash card (registered trademark), SmartMedia card, Memory Stick, MultiMediaCard, and PCM-CIA card. The examples also include (i) magnetic disks, such as a flexible disk, SuperDisk, Zip, and Clik! and (ii) a removable hard disk drive, such as ORB, Jaz, SparQ, SyJet, EZFley, and Microdrive.

10 [0135]

(B) Each of the above embodiments relates to the case where the playback apparatus decodes an AV clip stored on a BD-ROM and outputs the decoded AV clip to the television set. As an alternative, the playback apparatus may be equipped with a BD-ROM drive only and the remaining components are provided in the television set. In such a case, the playback apparatus and the television set can be incorporated into a home network connected with an IEEE 1394 connector. In addition, although the above embodiments relate to the playback apparatus connected to the television set, the playback apparatus may instead be integrally provided with a display. Also, the playback apparatus may include only the system LSI (integrated circuit) that carries out an essential part of the processing.

25 [0136]

(C) Information processing using the programs shown in the flowcharts is actually realized using hardware

resources. Accordingly, the programs, which describe the processing steps shown in the flowcharts, are themselves an invention. The above embodiments all relate to the case where the programs are incorporated in the playback apparatus, but the programs can be used independently of the playback apparatus. Acts of practicing the programs include (1) an act of manufacturing, (2) an act of assigning with or without charge, (3) an act of leasing, (4) an act of importing, (5) an act of providing to the public via a bi-directional electronic communications network, and (6) an act of offering for assignment or lease using storefront displays, catalogs, or brochures.

[0137]

(D) According to the above embodiments, the digital stream is an AV clip in compliance with the BD-ROM standard, but the present invention may also be applicable to a VOB (Video Object) of the DVD-Video standard or the DVD-Video Recording standard. The VOB is a program stream that complies with the ISO/IEC 13818-1 Standard and is obtained by multiplexing a video stream and an audio stream. Also, the video stream in the AV Clip may be an MPEG4 video stream or a WMV video stream. Further, the audio stream in the AV clip may be a Linear PCM audio stream, a Dolby AC-3 audio stream, an MP3 audio stream, an MPEG-AAC audio stream, or a dts audio stream.

[0138]

(E) According to the third embodiment, it is also applicable that all the pictures specified by the In\_time

of every PlayItem in PlayList information are IDR pictures.

### Industrial Applicability

[0139]

5       The recording medium and the playback apparatus according to the present invention may be employed for personal use in a home theater system, for example. Yet, the present invention may be manufactured in volume in accordance with the internal structures disclosed in the  
10   above embodiments. Thus, the recording medium and the playback apparatus of the present invention can be industrially manufactured or used on an industrial scale. In view of the above, the recording media and the playback apparatus of the present invention have industrial  
15   applicability.

### Brief Description Of The Drawings

[0140]

20       Fig. 1 illustrates a form of using a recording medium according to the present invention;

      Fig. 2 illustrates the internal structure of a BD-ROM;

      Fig. 3 schematically illustrates the structure of a file with the extension ".m2ts";

25       Fig. 4 illustrates a process through which TS packets carrying an AV clip are recorded onto the BD-ROM;

      Fig. 5A illustrates a plurality of pictures arranged in the coding order;

      Fig. 5B illustrates the GOP structure of the video

stream illustrated in Fig. 5A;

Fig. 6A illustrates the internal structure of a closed-GOP in the presentation order and in the coding order;

5 Fig. 6B illustrates the internal structure of an open-GOP;

Fig. 7A illustrates the internal structure of an IDR picture;

Fig. 7B illustrates the internal structure of a Non-IDR I picture;

10 Fig. 7C illustrates the dependencies between the Non-IDR I picture and other pictures;

Fig. 8 illustrates the dependencies that a Non-IDR I picture may have;

15 Fig. 9 illustrates a process through which an IDR or Non-IDR I picture is converted into TS packets;

Fig. 10 illustrates the internal structure of a piece of Clip information;

Fig. 11A illustrates Stream\_Coding\_Info associated with a video stream;

20 Fig. 11B illustrates Stream\_Coding\_Info associated with an audio stream;

Fig. 12 illustrates the concept of entering to an AV clip and exiting from the AV clip to another AV clip;

25 Fig. 13 illustrates the EP\_map setting associated with the video stream illustrated in Figs. 5A and 5B;

Fig. 14 shows, in tabular form, pairs of EP\_Low and EP\_High values representing the PTS\_EP\_start and the SPN\_EP\_start of entry points #1- #5 illustrated in Fig.

13;

Fig. 15 illustrates the range of data to be read to execute jump playback;

Fig. 16 illustrates the data structure of PlayList information;

Fig. 17 illustrates the relationship between an AV clip and PlayList information;

Fig. 18 illustrates the internal structure of a playback apparatus according to the present invention;

Fig. 19 illustrates the internal structure of a decoded picture buffer 10;

Fig. 20 illustrates a process of decoding a Non-IDR I picture by a video decoder 8;

Fig. 21 illustrates the contents stored in the decoded picture buffer 10 at the time of the IDR picture decoding;

Fig. 22 is a flowchart of a process of converting timing information into an I picture address;

Fig. 23 is a flowchart of the PL playback performed by a controller 44;

Fig. 24 illustrates an application layout implementing a multiangle section;

Fig. 25 illustrates the data structure of PlayList information;

Fig. 26A illustrates playback sections of a plurality of AV clips collectively specified by four Clip\_Information\_file\_name fields contained in PlayItem information;

[0141]



Fig. 26B illustrates extents of each AV clip on a PlayList timeline;

Fig. 27A is an allocation image showing the arrangement of the four AV clips constituting the multiangle section,  
5 on the BD-ROM;

Fig. 27B illustrates the internal structure of one extent of an AV clip;

Fig. 28 illustrates the concept of how to determine the contiguous length to the extent;

10 Fig. 29 illustrates the allocation of extents on the BD-ROM, along with the entry point setting;

Fig. 30 illustrates valid values of PSR(3) and the relationship with PlayItem and Clip information;

Fig. 31 is a flowchart of processing steps performed  
15 to execute playback of PlayList information according to a second embodiment of the present invention;

Fig. 32 is a flowchart of processing steps performed to read a multiangle section from a disc;

Fig. 33 illustrates a process of reading the BD-ROM  
20 for executing playback of an angle image A;

Fig. 34 illustrates a process of reading the BD-ROM performed upon receipt of a user operation of requesting an angle change;

Fig. 35 illustrates a process of reading the BD-ROM  
25 performed upon receipt of a user operation of requesting an angle change;

Fig. 36 illustrates the internal structure of PlayList information;

Fig. 37 illustrates chapters defined by PLMark information;

Fig. 38 illustrates pictures of a video stream used by PlayItem #1, together with the relevant part of entry\_map setting;

Fig. 39 illustrates pictures of a video stream used by PlayItem #2;

Fig. 40 illustrates pictures of a video stream used by PlayItem #3;

Fig. 41 is a flowchart of the processing steps for executing a chapter search function; and

Fig. 42 is a flowchart of the processing steps for executing a chapter skip function.

## Description of Reference Numerals

[0142]

- 1 BD Drive
- 2 Arrival Time Clock Counter
- 3 Source De-packetizer
- 4 PID Filter
- 5 Transport Buffer
- 6 Multiplexed Buffer
- 7 Coded Picture Buffer
- 8 Video Decoder
- 10 Decoded Picture Buffer
- 11 Video Plane
- 12 Transport Buffer
- 13 Coded Data Buffer

	14	Stream Graphics Processor
	15	Object Buffer
	16	Composition Buffer
	17	Composition Controller
5	18	Presentation Graphics Plane
	19	CLUT Unit
	20	Transport Buffer
	21	Coded Data Buffer
	22	Stream Graphics Processor
10	23	Object Buffer
	24	Composition Buffer
	25	Composition Controller
	26	Interactive Graphics Plane
	27	CLUT Unit
15	28	Compositor
	29	Compositor
	30	Switch
	31	Network Device
	32	Local Storage
20	33	Arrival Time Clock Counter
	34	Source De-Packetizer
	35	PID Filter
	36	Switch
	37	Transport Buffer
25	38	Elementary Buffer
	39	Audio Decoder
	40	Transport Buffer
	41	Buffer

42 Text Subtitle Decoder

43 Scenario Memory

44 Controller

46 PSR Set

5 100 BD-ROM

200 Playback Apparatus

300 Remote Controller

400 Television Set